

# FrenoStat 2000 + FrenoMat Brake Units



## FrenoStat 2000 Brake Units 380-430 V Line Voltage (50/60 Hz)

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000133	312 200 00	5.5 KW	36 AMP	Without
60000137	313 200 00	7.5 KW	60 AMP	Without
60000042	KS 0.075	5.5 KW + 7.5 KW	36 AMP + 60 AMP	Add / Optional
60000247	323 200 10	15 KW	100 AMP	Integrated
60000248	324 200 10	22 KW	150 AMP	Integrated
60000249	325 200 10	30 KW	200 AMP	Integrated
60000173	336 200 10	45 KW	300 AMP	KS 1.0
60000177	337 200 10	63 KW	400 AMP	KS 1.0
60000181	338 200 10	75 KW	500 AMP	KS 1.0
60000169	349 200 10	110 KW	750 AMP	KD 3.0
60000307	340 200 10	150 KW	1000 AMP	KD 4.0
60000308	350 200 10	200 KW	1500 AMP	KD 4.0
60000171	360 200 10	300 KW	2500 AMP	KD 4.0

## FrenoStat 2000 Brake Units 440-550 V Line Voltage (50/60 Hz)

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000135	312 300 00	7.5 KW	36 AMP	Without
60000138	313 300 00	11 KW	60 AMP	Without
60000042	KS 0.075	7.5 KW + 11 KW	36 AMP + 60 AMP	Add / Optional
60000250	323 300 10	18 KW	100 AMP	Integrated
60000251	324 300 10	30 KW	150 AMP	Integrated
60000252	325 300 10	37 KW	200 AMP	Integrated
60000174	336 300 10	55 KW	300 AMP	KS 1.0
60000179	337 300 10	75 KW	400 AMP	KS 1.0
60000182	338 300 10	110 KW	500 AMP	KS 1.0
60000164	349 300 10	150 KW	750 AMP	KD 3.0
60000167	340 300 10	200 KW	1000 AMP	KD 4.0

## FrenoMat 2 Brake Units / Line Voltage (50/60 Hz)

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000320	750 200 00	3 KW	30 AMP / 400 VOLT	Without
60000321	750 300 00	5.5 KW	30 AMP / 500 VOLT	Without
60000322	750 100 00	2.2 KW	30 AMP / 230 VOLT	Without

## Chokes / Line Conditioners

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000042	KS 0.075	3 to 11 KW	Up to 60 AMP	Add / Optional
60000045	KS 1.0	45 to 110 KW	Up to 500 AMP	Add / Optional

# FrenoStat 2000 + FrenoMat Brake Units



## FrenoStat 2000 Brake Units 230 V Line Voltage (50/60 Hz)

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000134	312 100 00	5.5 KW	36 AMP	Without
60000136	313 100 00	7.5 KW	60 AMP	Without
60000042	KS 0.075	5.5 KW + 7.5 KW	36 AMP + 60 AMP	Add / Optional
60000253	323 100 10	15 KW	100 AMP	Integrated
60000260	324 100 10	22 KW	150 AMP	Integrated
60000349	325 100 10	30 KW	200 AMP	Integrated
60000172	336 100 10	45 KW	300 AMP	KS 1.0
60000176	337 100 10	60 KW	400 AMP	KS 1.0
60000180	338 100 10	80 KW	500 AMP	KS 1.0

## FrenoStat 2000 Brake Units 600-700 V Line Voltage (50/60 Hz)

ORDER NO	TYPE NO	MAX. MOTOR POWER IN KW	MAX. DEVICE CURRENT	CHOKE
60000256	323 400 10	18 KW	100 AMP	Integrated
60000262	324 400 10	30 KW	150 AMP	Integrated
60000264	325 400 10	37 KW	200 AMP	Integrated
60000175	336 400 10	55 KW	300 AMP	KS 1.0
60000178	337 400 10	75 KW	400 AMP	KS 1.0
60000183	338 400 10	110 KW	500 AMP	KS 1.0

[ Copyright 2021© NovaMax Intl - Note: Dimensions, specifications and certifications may change without prior notification ]



### NovaMax Industrial LLC

8200 S Quebec St A-3 - Centennial CO 80112 USA

Phone : 303-470-7226 - Fax : 303-470-5773 - Toll-Free : 1-800-594-3380

Email : sales@novamaxindustrial.com - www.novamaxindustrial.com